

At Mission LED Lighting Company, we believe that every traditional bulb or tube converted to an LED is a step closer to a lighting solution that has a net-positive effect on the environment and your bottom line.



COMMON APPLICATIONS:

An excellent replacement for 4' T8 or T12 fluorescent tubes



LED Replacement Tubes

Mission Magic Tubes

PART # MS-TS-015-ZY

FEATURES:

- Works with the vast majority of T8 and T12 ballasts.
- Even light distribution with a 120 degree beam angle
- 50,000 hour lifespan, more than 10 years in most applications
- Design Lights Consortium approved with 5 year warranty
- Provides more light than a 32 watt fluorescent tube while reducing electrical consumption by 54%
- Compatible with most motion and light sensors
- Does not contain Mercury or other toxins

Product Specifications

Lamp Type	LED Replacement Tubes
Base	G13
Voltage (V)	100-347v w/ballast, 100 - 277v w/o ballast
Power (W)	15W
CCT	3 000K, 4 000K, 5 000K, 6 000K
CRI	>80
Beam Angle	120
Dimmable	No
Lumen	1 800
Lifespan (Hour)	50 000

LUMINOUS INTENSITY DISTRIBUTION DIAGRAM

